

定抵抗アッテネータの設計

減衰量	Z0 = 52 [Ω]		Z0 = 75 [Ω]		Z0 = 150 [Ω]		Z0 = 300 [Ω]		Z0 = 600 [Ω]		
	[dB]	R1	R2	R1	R2	R1	R2	R1	R2	R1	R2
1	910	6.2	1300	8.2	2400	16	5100	33	10000	68	
2	470	12	620	16	1200	33	2400	68	5100	130	
3	330	18	430	27	820	51	1600	100	3300	200	
4	220	24	330	36	620	68	1300	130	2700	270	
5	180	30	270	43	510	91	1000	180	2000	360	
6	150	39	220	56	430	110	910	220	1800	430	
7	130	47	180	62	360	130	750	270	1500	510	
8	120	56	160	75	330	150	680	300	1300	620	
9	110	68	150	91	300	180	620	360	1300	680	
10	100	75	150	100	270	200	560	390	1100	820	
11	91	82	130	120	270	240	510	470	1000	910	
12	82	100	120	130	240	270	470	510	910	1200	
13	82	110	110	150	220	300	430	620	820	1200	
14	75	130	110	180	220	330	430	680	820	1500	
15	75	150	100	200	200	390	430	750	820	1500	
16	68	160	100	220	200	430	390	910	820	1800	
17	68	180	91	240	200	510	390	1000	750	2000	
18	68	200	91	270	180	560	360	1100	750	2200	
19	68	220	91	330	180	620	360	1200	750	2400	
20	62	240	91	360	180	680	360	1500	680	2760	
30	56	820	75	1100	150	2400	330	4700	620	9100	
40	51	2400	75	3600	150	7500	330	15000	560	30000	

by JOINDG